



# Application Note: AZD033

## IQS127 Automatic soap dispenser application - IR replacement

### Table of Contents

|  |   |
|--|---|
| APPLICATION NOTE: AZD033 .....               | 1 |
| TABLE OF CONTENTS .....                      | 1 |
| 1 INTRODUCTION.....                          | 1 |
| 2 IR SENSOR REMOVAL .....                    | 1 |
| 3 IQS127 PROXSENSE™ SENSOR INTEGRATION ..... | 1 |
| 4 COMPARISON AND REFERENCE DESIGN.....       | 3 |

## 1 Introduction

This document describes the IR sensor replacement with an IQS127 ProxSense™ capacitive sensor, in an automatic soap dispenser application. The IQS127 is a cost effective single channel touch and proximity sensor offered in a TSOT23-6 package. For this study, an off-the-shelf soap dispenser was modified.

## 2 IR sensor removal

Two types of IR proximity detection are commonly employed, low range “always ON” infrared detection and long range pulsed infrared detection. Both infrared sensor types usually interface with a microcontroller, and can easily be replaced by a single ProxSense™ capacitive sensor in the majority of applications.




Figure 2.1 IR circuitry (top), ProxSense™ (bottom)

In the case of the soap dispenser, pulsed IR was employed. In Figure 2.1 the IR detection circuitry is compared to the ProxSense™ circuit board. The IR circuitry is easily removed at the interface to the microcontroller, as the detection circuitry simply outputs a LOW or HIGH signal in the event of a positive detection.

## 3 IQS127 ProxSense™ sensor integration

The IQS127 is extremely easy to set up and integrate into new and existing applications by following a few simple steps:

- Set up the IQS127 for active high or active low operation on detection (default active low).
- Design and integrate an appropriate sense antenna. (See section 3.1)
- Interface the IQS127 to a microcontroller or other control circuit.

The IQS127 requires very few external components; see section 4.2 for a typical design.


### 3.1 Integration of IQS127 and sense antenna

Due to its small size the IQS127 is easily and rapidly integrated into the automatic soap dispenser.



Figure 3.1 illustrates the integrated sense antenna inside the automatic soap dispenser, as well as the IQS127.


A passive ground plane can be used to shield areas where no proximity should be detected; in this case the lower sides or back of the soap dispenser, as can also be seen in Figure 3.1.



**Figure 3.1 Soap dispenser sense antenna and ground shield**

From the figure, the lower left, right and rear sides of the soap dispenser are shielded with a ground plane to prevent proximity detection in these directions. For more effective shielding ensure that the antenna sensing wire (Cx) is not resting directly against these planes, but at least 5mm away.

Other more compact ground shield configurations can be effectively used to achieve directionality and prevent unwanted detections at specific positions by etching them on a PCB in strategic locations such as illustrated in Figure 3.2.



**Figure 3.2 Azoteq soap dispenser sense antenna (yellow circle) and ground shields (black circles)**

The sense antenna depicted in figure 3.2 is mounted facing downwards and is an effective design that prevents false proximity detections from the sides of the soap dispenser.

The distance (dx) between the sense plate and ground shields is a key parameter, for the obtained sensing distance is directly proportional to the spacing between the electrodes. The implemented spacing (dx) was approximately 9mm.

It is also important to keep the IQS127 as close to this sense antenna as possible.


Should the sense antenna have a capacitance that is extremely low, the Automatic Tuning Implementation (ATI) of the IQS127 could fail to reach its target of 900, greatly diminishing the sensing range. In this case, the sensing antenna surface can be increased, or a discrete capacitance in the range of 2pF can be connected to the IQS127 Cx pin to ground to correct this problem.

## 3.2 Interfacing the IQS127 to a microcontroller

The IQS127 can be operated in active high or low modes depending on the desired application.

- Connect pin POUT of the IQS127 to any microcontroller input pin as usual, to signal proximity detection.

Figure 3.3 shows the connection of the IQS127 output to the automatic soap dispenser microcontroller PCB.



**Figure 3.3 Connection of IQS127 output to microcontroller PCB**



### 3.3 Final completed product

Figure 3.4 illustrates the completed automatic soap dispenser product in operation. Proximity detection is indicated in the figure by the bright blue lit LED.



**Figure 3.4 Completed automatic soap dispenser unit**

**Table 4.1 Comparison of ProxSense™ and IR sensing technologies**

|                            | <b>Azoteq Capacitive Sensing</b>      | <b>Infrared Proximity Sensing</b> |
|----------------------------|---------------------------------------|-----------------------------------|
| Device                     | IQS127x                               | Competing IR                      |
| Distance / Range           | 0mm~150mm                             | 0mm~150mm                         |
| Operating Voltage          | 1.8V~5V                               | 1.71V~3.6V                        |
| Power consumption          | 12uA                                  | 500uA~150mA                       |
| Controller Cost (US\$)     | Sub 0.16                              | 0.45~1.65                         |
| Sensing Electrode          | Can be copper foil or copper on a PCB | Requires translucent lens         |
| Tolerance to dirt build up | 100%                                  | Sensor will stop working.         |

## 4 Comparison and reference design

### 4.1 Advantages of ProxSense™ capacitive sensing over IR

This application note showed that it can be easily retro-fitted to IR units without requiring modification to the plastic housing. Main advantages of Azoteq capacitive proximity detection include the simplicity of implementation, low cost, robustness and extreme reliability, extremely low power consumption, and tolerance to dirt build up.

Table 4.1 forms a summary and comparison of the most important features of ProxSense™ capacitive sensing vs. IR sensing technologies.

From Table 4.1, the greatest advantage is the low power consumption, significantly extending the operating life of a battery power application like the soap dispenser, and the tolerance to dirt build up.


Moreover, ProxSense™ capacitive sensors can be integrated into much smaller volumes and confined spaces due to its minute size.

Taking into account all features and benefits, it is clear that ProxSense™ sensors provide impeccable flexibility and performance, and does so at a fraction of the cost of competing technologies.



## 4.2 Reference/Typical design


A typical design that can be used in the majority of applications is provided in Figure 4.1.



**Figure 4.1 Reference design**

The two outputs, Touch Output and Proximity Output, are illustrated in the figure. The two outputs are digital and can be set up to operate

in active HIGH or active LOW mode; they can simply be connected and interfaced to any microcontroller.



**ProxSense™: Adding  
AirButtons everywhere.**



## Contact Information

|                         | USA  | Asia  | South Africa   |
|-------------------------|--|---|--|
| <b>Physical Address</b> | 11940 Jollyville<br>Suite 120-S<br>Austin<br>TX 78759<br>USA | Room 501A, Block A,<br>T-Share International Centre,<br>Taoyuan Road, Nanshan District,<br>Shenzhen, Guangdong, PRC | 1 Bergsig Avenue<br>Paarl<br>7646<br>South Africa    |
| <b>Postal Address</b>   | 11940 Jollyville<br>Suite 120-S<br>Austin<br>TX 78750<br>USA | Room 501A, Block A,<br>T-Share International Centre,<br>Taoyuan Road, Nanshan District,<br>Shenzhen, Guangdong, PRC | PO Box 3534<br>Paarl<br>7620<br>South Africa         |
| <b>Tel</b>              | +1 512 538 1995  | +86 755 8303 5294<br>ext 808  | +27 21 863 0033                                      |
| <b>Email</b>            | <a href="mailto:info@azoteq.com">info@azoteq.com</a>         | <a href="mailto:info@azoteq.com">info@azoteq.com</a>  | <a href="mailto:info@azoteq.com">info@azoteq.com</a> |

[Visit www.azoteq.com](http://www.azoteq.com)

*for a list of distributors and worldwide representation.*

Patents as listed on [www.azoteq.com/patents-trademarks/](http://www.azoteq.com/patents-trademarks/) may relate to the device or usage of the device.

Azoteq®, Crystal Driver®, IQ Switch®, ProxSense®, ProxFusion®, LightSense™, SwipeSwitch™, and the  logo are trademarks of Azoteq.

The information in this Datasheet is believed to be accurate at the time of publication. Azoteq uses reasonable effort to maintain the information up-to-date and accurate, but does not warrant the accuracy, completeness or reliability of the information contained herein. All content and information are provided on an “as is” basis only, without any representations or warranties, express or implied, of any kind, including representations about the suitability of these products or information for any purpose. Azoteq disclaims all warranties and conditions with regard to these products and information, including but not limited to all implied warranties and conditions of merchantability, fitness for a particular purpose, title and non-infringement of any third party intellectual property rights. Azoteq assumes no liability for any damages or injury arising from any use of the information or the product or caused by, without limitation, failure of performance, error, omission, interruption, defect, delay in operation or transmission, even if Azoteq has been advised of the possibility of such damages. The applications mentioned herein are used solely for the purpose of illustration and Azoteq makes no warranty or representation that such applications will be suitable without further modification, nor recommends the use of its products for application that may present a risk to human life due to malfunction or otherwise. Azoteq products are not authorized for use as critical components in life support devices or systems. No licenses to patents are granted, implicitly, express or implied, by estoppel or otherwise, under any intellectual property rights. In the event that any of the abovementioned limitations or exclusions does not apply, it is agreed that Azoteq’s total liability for all losses, damages and causes of action (in contract, tort (including without limitation, negligence) or otherwise) will not exceed the amount already paid by the customer for the products. Azoteq reserves the right to alter its products, to make corrections, deletions, modifications, enhancements, improvements and other changes to the content and information, its products, programs and services at any time or to move or discontinue any contents, products, programs or services without prior notification. For the most up-to-date information and binding Terms and Conditions please refer to [www.azoteq.com](http://www.azoteq.com).